

Z-Wave Protocol Implementation Conformance Statement

A19 LED BULB RGBW

General Information

Product Identifier:	HA-ZW-5AQQ
Brand Name:	Aibase
Product Version:	HW: 0 FW: 2.00
Z-Wave Certification #:	ZC10-18056115

Product Features

Communications Protocol	Manufacturer Proprietary Protocol
Firmware Updatable	Updatable by Manufacturer

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0003
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.51.09
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 1	Z-Wave Plus Lifeline 1. When the state of the LED Bulb is changed, Sending Switch Multilevel Report to the associated nodes. 2. Sending Device Reset Locally CC to the associated nodes.

Z-Wave Protocol Implementation Conformance Statement

(Continued)

A19 LED BULB RGBW

Supported Command Classes (14):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V2
Manufacturer Specific V2	Powerlevel
Security S0	Switch All
Switch Color	Switch Multilevel V2
Version V2	Z-Wave Plus Info V2