

## Z-Wave Protocol Implementation Conformance Statement

# Z-Wave Floodlight with Motion Detector

### General Information

<b>Product Identifier:</b>	EH403-3
<b>Brand Name:</b>	Everspring
<b>Product Version:</b>	HW: 1 FW: 1.01:00.07
<b>Z-Wave Certification #:</b>	ZC10-18056122

### Product Features

<b>Sensors</b>	Luminance
<b>Color</b>	Black
<b>IP (Ingress Protection) Rated</b>	Yes
<b>Outdoor Use</b>	Yes
<b>Supported Notification Types</b>	Home Security

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0001
<b>Z-Wave Product Type:</b>	0x0012
<b>Z-Wave Hardware Platform:</b>	SD3502
<b>Z-Wave Development Kit Version:</b>	6.71.01
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Always On Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Z-Wave Floodlight with Motion Detector

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 1                    Command Class: -Device Reset Locally Notification -Notification Report -Binary Report -Sensor Multilevel

Report Group Name: Lifeline

2 / 4                    Command Class: -Basic Set Group Name: PIR Control

**Supported Command Classes (17):**

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Notification V4
Powerlevel	Security S0
Security S2	Sensor Multilevel V5
Supervision	Switch Binary
Transport Service V2	Version V2
Z-Wave Plus Info V2	

**Controlled Command Classes (1):**

Basic