

Z-Wave Protocol Implementation Conformance Statement

Plug-in Switch Mini

General Information

Product Identifier:	TZWP-102
Brand Name:	Telldus
Product Version:	HW: 1 FW: 1.00
Z-Wave Certification #:	ZC10-18036072

Product Features

Switch Type	Push Button
Z-Wave Scene Type	Scene
Switch Load Capacity Watts	2300
Supported Meter Type	Electric Energy
Firmware Updatable	Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0003
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.71.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Plug-in Switch Mini

Association Group Information

Group # / Max **Description**

Nodes

1 / 5 1. When the state of Smart Plug (turn on or off the load) is changed: 1. Set Configuration parameter 0x03 to 0: Do not send Basic Report 2. Set Configuration parameter 0x03 to 1: Send Basic Report 3. Set Configuration parameter 0x03 to 2: Send Basic Report only when Load condition is changed not by Z-WAVE Command, such as short pressing. 2. Sending Meter Report.

Supported Command Classes (19):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific	Manufacturer Specific V2
Meter V3	Powerlevel
Scene Activation	Scene Actuator Conf
Security S0	Security S2
Supervision	Switch Binary
Transport Service V2	Version V2
Z-Wave Plus Info V2	