

Z-Wave Protocol Implementation Conformance Statement

Nano Shutter

General Information

Product Identifier:	ZW141-B
Brand Name:	Aeotec
Product Version:	HW: 141 FW: 1.00:01.00
Z-Wave Certification #:	ZC10-18066131

Product Features

Firmware Updatable	Updatable by Consumer by RF
Window Covering Control Features	Endpoint Aware
Z-Wave Scene Type	Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	Australia / New Zealand
Z-Wave Product ID:	0x008D
Z-Wave Product Type:	0x0203
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.71.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Window Covering - No Position/Endpoint / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Nano Shutter

2 / 5 Forward the Basic Set, Binary Switch Set, Scene Activation Set to associated nodes in Group 2 when the Nano Shutter receives the Basic Set, Binary Switch Set, Scene Activation Set commands from main controller. (E.g. Send/forward Basic Set to control the other nodes in association Group 2)

Supported Command Classes (18):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Powerlevel
Scene Activation	Scene Actuator Conf
Security S0	Security S2
Supervision	Switch Binary
Switch Multilevel V3	Transport Service V2
Version V2	Z-Wave Plus Info V2

Controlled Command Classes (3):

Basic	Hail
Switch Binary	