

## Z-Wave Protocol Implementation Conformance Statement

### In Wall Dimmer

#### General Information

<b>Product Identifier:</b>	PAD07-3E
<b>Brand Name:</b>	ECO LIFE ENGINEERING
<b>Product Version:</b>	HW: 1 FW: 1.01
<b>Z-Wave Certification #:</b>	ZC10-18056108

#### Product Features

<b>Switch Load Capacity Current</b>	0.9A
<b>Neutral Wire Required</b>	Yes
<b>Z-Wave Scene Type</b>	Scene
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Color</b>	White

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	Japan
<b>Z-Wave Product ID:</b>	0x0063
<b>Z-Wave Product Type:</b>	0x0005
<b>Z-Wave Hardware Platform:</b>	SD3502
<b>Z-Wave Development Kit Version:</b>	6.51.09
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Light Dimmer Switch / Always On Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## In Wall Dimmer

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 5                      Lifeline The Switch can be set to send reports to associated Z-Wave devices. It supports one association group with five nodes support for grouping 1. For group 1, the dimmer will report MULTILEVEL\_SWITCH\_REPORT, ALARM\_REPORT and DEVICE\_RESET\_LOCALLY\_NOTIFICATION.

2 / 5                      Control\_Key1 When the On/Off status changes or the dim level is achieved manually, it will send BASIC\_SET command to group 2 nodes to make them unanimous.

**Supported Command Classes (15):**

- |                              |                          |
|------------------------------|--------------------------|
| Alarm                        | Association Group Info   |
| Association V2               | Basic                    |
| Configuration                | Device Reset Locally     |
| Firmware Update Meta-Data V2 | Manufacturer Specific V2 |
| Powerlevel                   | Scene Activation         |
| Scene Actuator Conf          | Security S0              |
| Switch Multilevel V2         | Version V2               |
| Z-Wave Plus Info V2          |                          |

**Controlled Command Classes (1):**

- Basic