

Z-Wave Protocol Implementation Conformance Statement

HomeSeer HS-FLS100+ Z-Wave Plus Floodlight Sensor

General Information

Product Identifier:	HS-FLS100+
Brand Name:	HomeSeer
Product Version:	HW: 1 FW: 1.02:00.00
Z-Wave Certification #:	ZC10-18076186

Product Features

Outdoor Use	Yes
Sensors	Luminance Motion/No Motion (Binary)
Supported Notification Types	Home Security Luminance
Firmware Updatable	Updatable by Consumer by RF
Electric Load Type	Incandescent LED

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x000B
Z-Wave Product Type:	0x0201
Z-Wave Hardware Platform:	SD3502
Z-Wave Development Kit Version:	6.71.03

Z-Wave Protocol Implementation Conformance Statement

(Continued)

HomeSeer HS-FLS100+ Z-Wave Plus Floodlight Sensor

Association Group Information

Group # / Max Description

Nodes

1 / 1 Z-Wave Plus Lifeline

2 / 4 PIR control

Supported Command Classes (17):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Notification V4
Powerlevel	Security S2
Sensor Binary	Sensor Multilevel V5
Supervision	Switch Binary
Transport Service V2	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Basic