

## Z-Wave Protocol Implementation Conformance Statement

# Z-Wave RGB Fan Controller

### General Information

<b>Product Identifier:</b>	HS-FC200+
<b>Brand Name:</b>	HomeSeer
<b>Product Version:</b>	HW: 255 FW: 50.01
<b>Z-Wave Certification #:</b>	ZC10-18066137

### Product Features

<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Load Capacity Current</b>	2.5 Amps
<b>Switch Load Capacity Volt-Ampere</b>	120 VAC
<b>Switch Load Capacity Watts</b>	300 Watts
<b>Neutral Wire Required</b>	Yes
<b>Outdoor Use</b>	No
<b>Switch Type</b>	Decorator Paddle Rocker
<b>Z-Wave Scene Type</b>	Scene & Central Scene
<b>Electric Load Type</b>	Inductive (e.g. Motor)

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Z-Wave RGB Fan Controller

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0001
<b>Z-Wave Product Type:</b>	0x0203
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.81.00
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Fan Switch / Always On Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5                    Z-Wave Plus Lifeline

**Supported Command Classes (17):**

Association Group Info	Association V2
Basic	Central Scene V3
Configuration V3	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Powerlevel	Scene Activation
Scene Actuator Conf	Security S2
Supervision	Switch Multilevel V4
Transport Service V2	Version V3
Z-Wave Plus Info V2	

**Controlled Command Classes (2):**

Central Scene V3	Supervision
------------------	-------------