

Z-Wave Protocol Implementation Conformance Statement

Door/Window Sensor

General Information

Product Identifier:	HS-DS100+
Brand Name:	HomeSeer
Product Version:	HW: 1 FW: 2.00
Z-Wave Certification #:	ZC10-18066165

Product Features

Battery Type	AAA
Sensors	Open/Closed (Binary)
Battery Quantity	2
Supported Notification Types	Access Control Home Security

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0008
Z-Wave Product Type:	0x0201
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Reporting Sleeping Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Door/Window Sensor

Association Group Information

Group # / Max **Description**

Nodes

1 / 5 Door/Window Sensor will send notification report and battery report to the associated nodes.

2 / 5 Sensor will send Basic Set to the associated nodes when the sensor body and magnet removed or combined.

Supported Command Classes (16):

- | | |
|--------------------------|------------------------------|
| Association Group Info | Association V2 |
| Battery | Configuration |
| Device Reset Locally | Firmware Update Meta-Data V4 |
| Manufacturer Specific V2 | Notification V8 |
| Powerlevel | Security S0 |
| Security S2 | Supervision |
| Transport Service V2 | Version V3 |
| Wake Up V2 | Z-Wave Plus Info V2 |

Controlled Command Classes (1):

Basic