

## Z-Wave Protocol Implementation Conformance Statement

### Plug-in Smart Switch, Dual Plug

#### General Information

<b>Product Identifier:</b>	28172/ZW4104
<b>Brand Name:</b>	Jasco Products Company
<b>Product Version:</b>	HW: 255 FW: 5.22
<b>Z-Wave Certification #:</b>	ZC10-18066169

#### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Electric Load Type</b>	Incandescent Inductive (e.g. Motor) LED

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3039
<b>Z-Wave Product Type:</b>	0x5052
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.10
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

#### Association Group Information

Group # / Max Nodes	Description
---------------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Plug-in Smart Switch, Dual Plug

- 2 / 5 Supports Basic Set and is controlled with the local load.
- 3 / 5 Supports basic set and is controlled by double pressing the button.

### Supported Command Classes (14):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V2
Manufacturer Specific V2	Powerlevel
Scene Activation	Scene Actuator Conf
Switch All	Switch Binary
Version V2	Z-Wave Plus Info V2

### Controlled Command Classes (1):

Basic