

## Z-Wave Protocol Implementation Conformance Statement

### Smart Door Sensor

#### General Information

<b>Product Identifier:</b>	HS3DS-Z
<b>Brand Name:</b>	HEIMAN
<b>Product Version:</b>	HW: 255 FW: 3.01
<b>Z-Wave Certification #:</b>	ZC10-18106248

#### Product Features

<b>Battery Type</b>	CR2
<b>Color</b>	White
<b>Communications Protocol</b>	Z-Wave Serial API
<b>Supported Notification Types</b>	Access Control Emergency Alarm Home Security Irrigation
<b>Battery Quantity</b>	1PC

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0168
<b>Z-Wave Product Type:</b>	0x0168
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.71.03

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Smart Door Sensor

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5                Lifeline association group  
2 / 5                Root Device group(Basic set)

**Supported Command Classes (14):**

Association Group Info	Association V2
Battery	Device Reset Locally
Manufacturer Specific V2	Multi-Channel Association V3
Notification V8	Powerlevel
Security S2	Supervision
Transport Service V2	Version V3
Wake Up V2	Z-Wave Plus Info V2

**Controlled Command Classes (1):**

Basic V2