

## Z-Wave Protocol Implementation Conformance Statement

### Smart Boost Timer Switch

#### General Information

<b>Product Identifier:</b>	ZWA006-C
<b>Brand Name:</b>	Aeotec
<b>Product Version:</b>	HW: 2 FW: 1.00:01.00
<b>Z-Wave Certification #:</b>	ZC10-18106255

#### Product Features

<b>Switch Type</b>	Push Button
<b>Switch Load Capacity Current</b>	16A
<b>Supported Meter Type</b>	Electric Energy
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Load Capacity Volt-Ampere</b>	220V 16A
<b>Battery Quantity</b>	1
<b>Battery Type</b>	CR2032
<b>Color</b>	White
<b>Sensors</b>	Power
<b>Switch Load Capacity Watts</b>	3680W
<b>Electric Load Type</b>	Incandescent
<b>Neutral Wire Required</b>	Yes

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Smart Boost Timer Switch

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x00B4
<b>Z-Wave Product Type:</b>	0x0003
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.81.01
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 5            COMMAND\_CLASS\_SWITCH\_BINARY/SWITCH\_BINARY\_REPORT  
COMMAND\_CLASS\_METER\_V5/METER\_REPORT\_V5  
COMMAND\_CLASS\_CLOCK/CLOCK\_REPORT  
COMMAND\_CLASS\_SENSOR\_MULTILEVEL\_V11/SENSOR\_MULTILEVEL\_REPORT\_V11  
COMMAND\_CLASS\_SCHEDULE/SCHEDULE\_STATE\_REPORT  
COMMAND\_CLASS\_DEVICE\_RESET\_LOCALLY/DEVICE\_RESET\_LOCALLY\_NOTIFICATION

**Supported Command Classes (20):**

3ET

Association Group Info	Association V2
Basic V2	Clock
Configuration	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Meter V5	Multi-Channel Association V3
Powerlevel	Schedule
Security S0	Security S2
Sensor Multilevel V11	Supervision
Switch Binary	Transport Service V2
Version V3	Z-Wave Plus Info V2

**Controlled Command Classes (1):**

Basic V2