

## Z-Wave Protocol Implementation Conformance Statement

### Heatit Z-Water

#### General Information

<b>Product Identifier:</b>	Z-Water
<b>Brand Name:</b>	Heatit controls
<b>Product Version:</b>	HW: 2 FW: 2.01
<b>Z-Wave Certification #:</b>	ZC10-19036400

#### Product Features

<b>Switch Load Capacity Watts</b>	150W
<b>Switch Load Capacity Current</b>	5A
<b>Switch Load Capacity Volt-Ampere</b>	150 VA
<b>Loads Controlled</b>	10
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Supported Notification Types</b>	(No feature option values set for this feature)
<b>Electric Load Type</b>	Dimmable ELV (Magnetic) Dimmable Fluorescent Dimmable LED Dimmable MLV (Magnetic) ELV (Electronic) Fluorescent Incandescent Inductive (e.g. Motor) LED MLV (Magnetic)
<b>Sensors</b>	Air Temperature

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
-------------------------------------	-----

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

Heatit Z-Water

## Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x020A
<b>Z-Wave Product Type:</b>	0x0003
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.71.03
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Valve / Always On Slave

## Association Group Information

**Group # / Max    Description**

### Nodes

1 / 5	Lifeline. - Reset notification - Basic Report On / Off - Multilevel Sensor Report
2 / 5	Sends Multilevel Sensor Reports for input 1.
3 / 5	Sends Multilevel Sensor Reports for input 2.
4 / 5	Sends Multilevel Sensor Reports for input 3.
5 / 5	Sends Multilevel Sensor Reports for input 4.

### Supported Command Classes (19):

Association Group Info	Association V2
Basic V2	Battery
Configuration V3	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Multi-Channel Association V3	Multi-Channel V4
Powerlevel	Security S0
Security S2	Sensor Multilevel V5
Supervision	Switch Binary
Transport Service V2	Version V3
Z-Wave Plus Info V2	