

Z-Wave Protocol Implementation Conformance Statement

Z-Wave Plus Double Plug

General Information

Product Identifier:	ZW47
Brand Name:	Zooz
Product Version:	HW: 255 FW: 1.00
Z-Wave Certification #:	ZC10-18116324

Product Features

Supported Notification Types	Power Management
Switch Load Capacity Watts	1800W
Firmware Updatable	Updatable by Consumer by RF
Switch Load Capacity Current	15A
Electric Load Type	Fluorescent Incandescent Inductive (e.g. Motor) LED
Supported Meter Type	Electric Energy
Color	White

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Wave Plus Double Plug

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0xA003
Z-Wave Product Type:	0xA000
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.71.03
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max	Description
----------------------	--------------------

Nodes

1 / 1	Z-Wave Plus Lifeline
2 / 5	basic set command When the output of the ZW47 Endpoint1 socket is changed, On (0xFF) or Off (0x00) or Overload, The ZW47 will automatically send out a related basic set command. On (0xFF) or Off (0x00) to its associated group.
3 / 5	basic set command When the output of the ZW47 Endpoint2 socket is changed, On (0xFF) or Off (0x00) or Overload, The ZW47 will automatically send out a related basic set command. On (0xFF) or Off (0x00) to its associated group.