

Z-Wave Protocol Implementation Conformance Statement

Schlage Connect Smart Deadbolt

General Information

| | |
|--------------------------------|----------------------|
| Product Identifier: | BE469ZP |
| Brand Name: | Schlage |
| Product Version: | HW: 3 FW: 3.03:10.09 |
| Z-Wave Certification #: | ZC10-18106281 |

Product Features

| | |
|-------------------------------------|--|
| Battery Type | AA |
| Battery Quantity | 4 |
| Supported Notification Types | Access Control Power Management System |
| Door Lock Type | Deadbolt |

Z-Wave Product Information

| | |
|--------------------------------------|------------------------|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | Yes |
| Supports Security S2? | Yes: S2 Access Control |
| SmartStart Compatible? | Yes |

Z-Wave Technical Information

| | |
|--|---|
| Z-Wave Frequency: | U.S. / Canada / Mexico |
| Z-Wave Product ID: | 0x0469 |
| Z-Wave Product Type: | 0x0001 |
| Z-Wave Hardware Platform: | ZM5101 |
| Z-Wave Development Kit Version: | 6.81.02 |
| Z-Wave Library Type: | Routing Slave |
| Z-Wave Device Type / Role Type: | Door Lock - Keypad / Listening Sleeping Slave |

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Schlage Connect Smart Deadbolt

Association Group Information

Group # / Max Description

Nodes

1 / 2 Z-Wave Lifeline

Supported Command Classes (21):

| | |
|------------------------------|------------------------|
| Anti-Theft V2 | Association Group Info |
| Association V2 | Basic |
| Battery | Configuration |
| Device Reset Locally | Door Lock V2 |
| Firmware Update Meta-Data V3 | Manufacturer Specific |
| Notification V8 | Powerlevel |
| Schedule Entry Lock V3 | Security S0 |
| Security S2 | Supervision |
| Time | Transport Service V2 |
| User Code | Version V2 |
| Z-Wave Plus Info V2 | |

Controlled Command Classes (1):

Time