

## Z-Wave Protocol Implementation Conformance Statement

### Indoor Voice Siren

#### General Information

<b>Product Identifier:</b>	SE813-1
<b>Brand Name:</b>	Everspring
<b>Product Version:</b>	HW: 1 FW: 1.03:00.01
<b>Z-Wave Certification #:</b>	ZC10-18116293

#### Product Features

<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Supported Notification Types</b>	Siren
<b>Battery Type</b>	LR14
<b>Sensors</b>	Air Temperature
<b>Battery Quantity</b>	4

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0003
<b>Z-Wave Product Type:</b>	0x000C
<b>Z-Wave Hardware Platform:</b>	SD3502
<b>Z-Wave Development Kit Version:</b>	6.71.03
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Indoor Voice Siren

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 5                    Z-Wave Plus Lifeline

**Supported Command Classes (19):**

Association Group Info	Association V2
Basic	Battery
Configuration	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Notification V8	Powerlevel
Security S0	Security S2
Sensor Multilevel V5	Sound Switch
Supervision	Switch Binary
Transport Service V2	Version V3
Z-Wave Plus Info V2	