



## Z-Wave Protocol Implementation Conformance Statement

### Smart Dimmer Plug

#### General Information

**Product Identifier:** PAD09-4  
**Brand Name:** Philio Technology  
**Product Version:** HW: 1 FW: 1.01  
**Z-Wave Certification #:** ZC10-18126332

#### Product Features

**Firmware Updatable** Updatable by Manufacturer  
**Supported Notification Types** Power Management

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes  
Supports Z-Wave Network Security? Yes  
Supports Z-Wave AES-128 Security S0? Yes  
Supports Security S2? Yes: S2 Unauthenticated  
SmartStart Compatible? Yes

#### Z-Wave Technical Information

**Z-Wave Frequency:** CEPT (Europe)  
**Z-Wave Product ID:** 0x0060  
**Z-Wave Product Type:** 0x0005  
**Z-Wave Hardware Platform:** SD3502  
**Z-Wave Development Kit Version:** 6.81.01  
**Z-Wave Library Type:** Enhanced 232 Slave  
**Z-Wave Device Type / Role Type:** Light Dimmer Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
<b>Nodes</b>	
1 / 5	Group 1 name:Lifename Group 1 command list: COMMAND_CLASS_SWITCH_MULTILEVEL_V2, COMMAND_CLASS_NOTIFICATION_V8, COMMAND_CLASS_DEVICE_RESET_LOCALLY

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Smart Dimmer Plug

2 / 5            Group 2 name:Control Key1 Group 2 command list: COMMAND\_CLASS\_BASIC\_SET,

### Supported Command Classes (18):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Notification V8
Powerlevel	Scene Activation
Scene Actuator Conf	Security S0
Security S2	Supervision
Switch Multilevel V2	Transport Service V2
Version V3	Z-Wave Plus Info V2

### Controlled Command Classes (1):

Basic