

## Z-Wave Protocol Implementation Conformance Statement

### Slim Smart Door/Window Sensor

#### General Information

<b>Product Identifier:</b>	43973/ZW6305
<b>Brand Name:</b>	Jasco Products Company
<b>Product Version:</b>	HW: 255 FW: 5.55
<b>Z-Wave Certification #:</b>	ZC10-19016363

#### Product Features

<b>Battery Type</b>	CR2450
<b>Supported Notification Types</b>	Home Security
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Battery Quantity</b>	1
<b>Sensors</b>	Open/Closed (Binary)

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3235
<b>Z-Wave Product Type:</b>	0x4953
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.81.01
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Slim Smart Door/Window Sensor

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5                    Z-Wave Plus Lifeline

**Supported Command Classes (15):**

Association Group Info	Association V2
Battery	Configuration V4
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Notification V8
Powerlevel	Security S2
Supervision	Transport Service V2
Version V3	Wake Up V2
Z-Wave Plus Info V2	