



## Z-Wave Protocol Implementation Conformance Statement

### 1 Touch Panel Switch

#### General Information

<b>Product Identifier:</b>	HTP-1S0
<b>Brand Name:</b>	Hogar Controls
<b>Product Version:</b>	HW: 255 FW: 2.50
<b>Z-Wave Certification #:</b>	ZC10-19046451

#### Product Features

<b>Firmware Updatable</b>	Updatable by Professional/Technician
<b>Electric Load Type</b>	Dimmable ELV (Magnetic) Dimmable Fluorescent Dimmable LED Dimmable MLV (Magnetic) ELV (Electronic) Fluorescent Incandescent Inductive (e.g. Motor) LED MLV (Magnetic)
<b>Switch Load Capacity Watts</b>	700
<b>Neutral Wire Required</b>	Yes
<b>Switch Load Capacity Current</b>	3

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## 1 Touch Panel Switch

### Z-Wave Technical Information

Z-Wave Frequency:	Australia / New Zealand
Z-Wave Product ID:	0x4411
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

### Association Group Information

Group # / Max	Description
<b>Nodes</b>	
1 / 5	Name: Lifeline Command: - Device Reset Locally Notification - Switch Binary Report
2 / 5	Name: HGT-01 Command: - Basic Set Device support control another device through root device association group #2~#3, and each group support 5 destination nodes maximum.
3 / 5	Name: HGT-01 Command: - Switch Binary Set Device support control another device through root device association group #2~#3, and each group support 5 destination nodes maximum.

#### Supported Command Classes (14):

Association Group Info	Association V2
Basic	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Multi-Channel Association V3	Powerlevel
Security S2	Supervision
Switch Binary	Transport Service V2
Version V3	Z-Wave Plus Info V2

#### Controlled Command Classes (2):

Basic	Switch Binary
-------	---------------