

## Z-Wave Protocol Implementation Conformance Statement

### Smart Station

#### General Information

<b>Product Identifier:</b>	Model LS090WH
<b>Brand Name:</b>	Hangzhou Lifesmart Technology Co., Ltd.
<b>Product Version:</b>	HW: 1 FW: 1.01:01.01:00.00
<b>Z-Wave Certification #:</b>	ZC10-19036392

#### Product Features

<b>Communications Protocol</b>	Z-Wave Serial API
<b>Firmware Updatable</b>	Updatable by Consumer via Internet
<b>Gateway Has Preferred Partners</b>	No
<b>Color</b>	White
<b>Communications Connections</b>	Ethernet (Wired)

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control, S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	Japan
<b>Z-Wave Product ID:</b>	0x0001
<b>Z-Wave Product Type:</b>	0x0001
<b>Z-Wave Hardware Platform:</b>	ZM5304
<b>Z-Wave Development Kit Version:</b>	6.81.04
<b>Z-Wave Library Type:</b>	Static Controller
<b>Z-Wave Device Type / Role Type:</b>	Gateway / Central Static Controller

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart Station

## Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5                    Z-Wave Plus Lifeline

**Supported Command Classes (14):**

Association Group Info	Association V2
CRC16 Encapsulation	Device Reset Locally
Inclusion Controller	Manufacturer Specific
Multi Channel Association V2	Powerlevel
Security S0	Security S2
Supervision	Transport Service V2
Version V2	Z-Wave Plus Info V2

**Controlled Command Classes (15):**

Association V2	Basic
Battery	CRC16 Encapsulation
Door Lock	Manufacturer Specific
Multi-Channel V4	Powerlevel
Security S0	Security S2
Switch Binary	Switch Multilevel V3
Version V2	Wake Up V2
Z-Wave Plus Info V2	