



## Z-Wave Protocol Implementation Conformance Statement

### NanoMote Quad

#### General Information

<b>Product Identifier:</b>	ZWA003-S
<b>Brand Name:</b>	Aeotec
<b>Product Version:</b>	HW: 1 FW: 1.02
<b>Z-Wave Certification #:</b>	ZC10-19036389

#### Product Features

<b>Battery Quantity</b>	1
<b>Battery Type</b>	LIR2450
<b>Firmware Updatable</b>	Updatable by Consumer via Internet
<b>Z-Wave Scene Type</b>	Scene & Central Scene

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	Singapore
<b>Z-Wave Product ID:</b>	0x0003
<b>Z-Wave Product Type:</b>	0x1C02
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.71.01
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Wall Controller / Portable Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

NanoMote Quad

## Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5	Lifeline
2 / 5	On/Off control,Button 1
3 / 5	Dimming control,Button 1
4 / 5	On/Off control,Button 2
5 / 5	Dimming control,Button 2
6 / 5	On/Off control,Button 3
7 / 5	Dimming control,Button 3
8 / 5	On/Off control,Button 4
9 / 5	Dimming control,Button 4

**Supported Command Classes (16):**

Command Class Association Group Info	Command Class Association V2
Command Class Battery	Command Class Central Scene V3
Command Class Configuration	Command Class Device Reset Locally
Command Class Firmware Update Md V3	Command Class Manufacturer Specific V2
Command Class Powerlevel	Command Class Security
Command Class Security 2	Command Class Supervision
Command Class Transport Service V2	Command Class Version V2
Command Class Wake Up V2	Command Class Z-Wave+ Info V2

**Controlled Command Classes (3):**

Command Class Basic	Command Class Battery
Command Class Switch Multilevel V2	