



Z-Wave Protocol Implementation Conformance Statement

Danalock V3-BTZH-JP

General Information

Product Identifier:	Danalock V3-BTZH-JP
Brand Name:	Danalock
Product Version:	HW: 2 FW: 1.03:00.10
Z-Wave Certification #:	ZC10-19046422

Product Features

Supported Notification Types	Access Control
Battery Type	CR123
Firmware Updatable	Updatable by Consumer by RF
Battery Quantity	4

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	Japan
Z-Wave Product ID:	0x0001
Z-Wave Product Type:	0x0009
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.71.03
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Door Lock - Keypad / Listening Sleeping Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Danalock V3-BTZH-JP

Association Group Information

Group # / Max **Description**

Nodes

1 / 1 Z-Wave Plus Lifeline • Device Reset Locally: triggered upon reset. • Battery/notification: triggered upon low battery. • Door Lock operation report: triggered upon a change in door lock • Notification: triggered upon a change in door lock

Supported Command Classes (20):

Association Group Info	Association V2
Battery	Configuration
Device Reset Locally	Door Lock V2
Firmware Update Meta-Data V4	Manufacturer Specific V2
Notification V8	Powerlevel
Schedule Entry Lock V3	Security S0
Security S2	Supervision
Time	Time Parameters
Transport Service V2	User Code
Version V2	Z-Wave Plus Info V2