

## Z-Wave Protocol Implementation Conformance Statement

# In-Wall Smart Toggle Dimmer

### General Information

**Product Identifier:** 14295/46204/ZW3011  
**Brand Name:** GE  
**Product Version:** HW: 255 FW: 5.53  
**Z-Wave Certification #:** ZC10-19056483

### Product Features

**Neutral Wire Required** Yes

**Firmware Updatable** Updatable by Consumer by RF

**Z-Wave Scene Type** Central Scene

### Z-Wave Product Information

**Supports Z-Wave Beaming Technology?** Yes  
**Supports Z-Wave Network Security?** Yes  
**Supports Z-Wave AES-128 Security S0?** No  
**Supports Security S2?** Yes: S2 Authenticated, S2 Unauthenticated  
**SmartStart Compatible?** Yes

### Z-Wave Technical Information

**Z-Wave Frequency:** U.S. / Canada / Mexico  
**Z-Wave Product ID:** 0x3237  
**Z-Wave Product Type:** 0x4944  
**Z-Wave Hardware Platform:** ZM5202  
**Z-Wave Development Kit Version:** 6.81.03  
**Z-Wave Library Type:** Enhanced 232 Slave  
**Z-Wave Device Type / Role Type:** Light Dimmer Switch / Always On Slave

### Association Group Information

Group # / Max Nodes	Description
---------------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## In-Wall Smart Toggle Dimmer

2 / 5 Supports Basic Set and is controlled by pressing the ON or OFF button with the local load

3 / 5 Supports Basic Set and is controlled by double pressing the ON or OFF button

### Supported Command Classes (16):

Application Status	Association Group Info
Association V2	Basic V2
Central Scene V3	Configuration V4
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Powerlevel
Security S2	Supervision
Switch Multilevel V4	Transport Service V2
Version V3	Z-Wave Plus Info V2

### Controlled Command Classes (1):

Basic V2