

## Z-Wave Protocol Implementation Conformance Statement

# WALL SWITCH-ON/OFF BUTTON

### General Information

<b>Product Identifier:</b>	AC137-1
<b>Brand Name:</b>	Everspring
<b>Product Version:</b>	HW: 1 FW: 1.01
<b>Z-Wave Certification #:</b>	ZC10-19056482

### Product Features

<b>Battery Quantity</b>	2
<b>Color</b>	White
<b>Supported Notification Types</b>	Appliance
<b>Switch Type</b>	Push Button
<b>Battery Type</b>	AAA

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0003
<b>Z-Wave Product Type:</b>	0x000A
<b>Z-Wave Hardware Platform:</b>	SD3502
<b>Z-Wave Development Kit Version:</b>	6.71.03
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Wall Controller / Reporting Sleeping Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## WALL SWITCH-ON/OFF BUTTON

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 1	Z-Wave Plus Lifeline
2 / 4	Button 1
3 / 4	Button 2

**Supported Command Classes (17):**

Association Group Info	Association V2
Battery	Central Scene V3
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Multi-Channel Association V3
Notification V8	Powerlevel
Security S0	Security S2
Supervision	Transport Service V2
Version V3	Wake Up V2
Z-Wave Plus Info V2	

**Controlled Command Classes (1):**

Basic