

Z-Wave Protocol Implementation Conformance Statement

Smart Smoke Alarm

General Information

Product Identifier: 51114
Brand Name: CLEVERIO
Product Version: HW: 255 FW: 3.01
Z-Wave Certification #: ZC10-19056486

Product Features

Battery Type CR17335/CR123A
Color White
Supported Notification Types Smoke Alarm

Z-Wave Product Information

Supports Z-Wave Beaming Technology? No
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? No
Supports Security S2? Yes: S2 Unauthenticated
SmartStart Compatible? No

Z-Wave Technical Information

Z-Wave Frequency: CEPT (Europe)
Z-Wave Product ID: 0x1000
Z-Wave Product Type: 0x8002
Z-Wave Hardware Platform: ZM5202
Z-Wave Development Kit Version: 6.71.03
Z-Wave Library Type: Routing Slave
Z-Wave Device Type / Role Type: Notification Sensor / Reporting Sleeping Slave

Association Group Information

Group # / Max Description
Nodes

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart Smoke Alarm

2 / 5 The Sensor sends a Basic Set command to directly trigger devices (like a light, switch, etc.) in response to events. The value of the Basic Set command (e.g. Siren trigger) is configured using smoke or no smoke

Supported Command Classes (16):

Association Group Info	Association V2
Battery	Device Reset Locally
Manufacturer Specific	Manufacturer Specific V2
Multi-Channel Association V3	Notification V8
Powerlevel	Security S2
Supervision	Transport Service V2
Version V2	Version V3
Wake Up V2	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic V2