

## Z-Wave Protocol Implementation Conformance Statement

### Smart Smoke Alarm

#### General Information

**Product Identifier:** 51114  
**Brand Name:** CLEVERIO  
**Product Version:** HW: 255 FW: 3.01  
**Z-Wave Certification #:** ZC10-19056486

#### Product Features

**Battery Type** CR17335/CR123A  
**Color** White  
**Supported Notification Types** Smoke Alarm

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology? No  
Supports Z-Wave Network Security? Yes  
Supports Z-Wave AES-128 Security S0? No  
Supports Security S2? Yes: S2 Unauthenticated  
SmartStart Compatible? No

#### Z-Wave Technical Information

**Z-Wave Frequency:** CEPT (Europe)  
**Z-Wave Product ID:** 0x1000  
**Z-Wave Product Type:** 0x8002  
**Z-Wave Hardware Platform:** ZM5202  
**Z-Wave Development Kit Version:** 6.71.03  
**Z-Wave Library Type:** Routing Slave  
**Z-Wave Device Type / Role Type:** Notification Sensor / Reporting Sleeping Slave

#### Association Group Information

**Group # / Max Description**  
**Nodes**

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Smart Smoke Alarm

2 / 5            The Sensor sends a Basic Set command to directly trigger devices (like a light, switch, etc.) in response to events. The value of the Basic Set command (e.g. Siren trigger) is configured using smoke or no smoke

### Supported Command Classes (16):

Association Group Info	Association V2
Battery	Device Reset Locally
Manufacturer Specific	Manufacturer Specific V2
Multi-Channel Association V3	Notification V8
Powerlevel	Security S2
Supervision	Transport Service V2
Version V2	Version V3
Wake Up V2	Z-Wave Plus Info V2

### Controlled Command Classes (1):

Basic V2