

## Z-Wave Protocol Implementation Conformance Statement

# Plug-in Outdoor Smart Switch

### General Information

**Product Identifier:** 14298/ZW4202  
**Brand Name:** GE  
**Product Version:** HW: 255 FW: 5.52  
**Z-Wave Certification #:** ZC10-19066524

### Product Features

**Firmware Updatable** Updatable by Consumer by RF  
**Z-Wave Scene Type** Central Scene

### Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes  
Supports Z-Wave Network Security? Yes  
Supports Z-Wave AES-128 Security S0? No  
Supports Security S2? Yes: S2 Authenticated, S2 Unauthenticated  
SmartStart Compatible? Yes

### Z-Wave Technical Information

**Z-Wave Frequency:** U.S. / Canada / Mexico  
**Z-Wave Product ID:** 0x3034  
**Z-Wave Product Type:** 0x4F50  
**Z-Wave Hardware Platform:** ZM5202  
**Z-Wave Development Kit Version:** 6.81.03  
**Z-Wave Library Type:** Enhanced 232 Slave  
**Z-Wave Device Type / Role Type:** On/Off Power Switch / Always On Slave

### Association Group Information

Group # / Max	Description
<b>Nodes</b>	
1 / 5	Z-Wave Plus Lifeline
2 / 5	Supports Basic Set and is controlled by pressing the ON or OFF button with the local load.

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Plug-in Outdoor Smart Switch

### Supported Command Classes (18):

Application Status	Association Group Info
Association V2	Basic V2
Central Scene V3	Configuration V4
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Powerlevel
Scene Activation	Scene Actuator Conf
Security S2	Supervision
Switch Binary V2	Transport Service V2
Version V3	Z-Wave Plus Info V2

### Controlled Command Classes (1):

Basic V2