

## Z-Wave Protocol Implementation Conformance Statement

### 2-Channel Dimmer

#### General Information

<b>Product Identifier:</b>	CT2D
<b>Brand Name:</b>	CONFIO
<b>Product Version:</b>	HW: 1 FW: 1.00
<b>Z-Wave Certification #:</b>	ZC10-19096735

#### Product Features

<b>Loads Controlled</b>	2
<b>Switch Load Capacity Watts</b>	300
<b>Neutral Wire Required</b>	Yes
<b>Firmware Updatable</b>	Updatable by Manufacturer
<b>Electric Load Type</b>	Dimmable ELV (Magnetic) Dimmable LED Dimmable MLV (Magnetic) Incandescent LED

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	Yes

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## 2-Channel Dimmer

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	India
<b>Z-Wave Product ID:</b>	0xC002
<b>Z-Wave Product Type:</b>	0x4000
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.81.03
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Light Dimmer Switch / Always On Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 3                Z-Wave Plus Lifeline

**Supported Command Classes (17):**

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Multi-Channel Association V3
Multi-Channel V4	Powerlevel
Security S0	Security S2
Supervision	Switch Multilevel
Transport Service V2	Version V3
Z-Wave Plus Info V2	