

## Z-Wave Protocol Implementation Conformance Statement

### On/Off Switch

#### General Information

<b>Product Identifier:</b>	LZW30
<b>Brand Name:</b>	Inovelli
<b>Product Version:</b>	HW: 1 FW: 2.00
<b>Z-Wave Certification #:</b>	ZC10-19086701

#### Product Features

<b>Switch Load Capacity Watts</b>	600
<b>Firmware Updatable</b>	Updatable by Manufacturer

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0001
<b>Z-Wave Product Type:</b>	0x0004
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.81.03
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
<b>Nodes</b>	
1 / 5	1. Basic Report 2. Device Reset Locally 3. Protection Report
2 / 5	Basic Set

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## On/Off Switch

### Supported Command Classes (17):

Application Status	Association Group Info
Association V2	Basic
Configuration	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Powerlevel	Protection V2
Security S0	Security S2
Supervision	Switch Binary
Transport Service V2	Version V2
Z-Wave Plus Info V2	

### Controlled Command Classes (1):

Basic