

Z-Wave Protocol Implementation Conformance Statement

Recessed Door Sensor

General Information

Product Identifier:	PSM09-A
Brand Name:	Philio
Product Version:	HW: 255 FW: 0.10
Z-Wave Certification #:	ZC10-19066570

Product Features

Sensors	Open/Closed (Binary)
Firmware Updatable	Updatable by Consumer by RF
Supported Notification Types	Access Control Home Security
Battery Quantity	1
Battery Type	ER14250

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x006A
Z-Wave Product Type:	0x0002
Z-Wave Hardware Platform:	SD3502
Z-Wave Development Kit Version:	6.81.04
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Reporting Sleeping Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Recessed Door Sensor

Association Group Information

Group # / Max **Description**

Nodes

1 / 5 Z-Wave Plus Lifeline This machine provides a group of groups. Each group can set 5 Nodes. Group 1: Used for event return. Report type: 1. Door sensor state 2.Battery state 3.Reset report

Supported Command Classes (17):

Association Group Info	Association V2
Battery	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Multi-Channel Association V3
Notification V8	Powerlevel
Security S0	Security S2
Supervision	Transport Service V2
Version V3	Wake Up V2
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Notification V8