

## Z-Wave Protocol Implementation Conformance Statement

### Door/Window Sensor 7

#### General Information

|                                |                |
|--------------------------------|----------------|
| <b>Product Identifier:</b>     | ZWA008-C       |
| <b>Brand Name:</b>             | Aeotec         |
| <b>Product Version:</b>        | HW: 1 FW: 1.00 |
| <b>Z-Wave Certification #:</b> | ZC10-19066568  |

#### Product Features

|                                     |   |
|-------------------------------------|---|
| <b>Battery Quantity</b>             | 1   |
| <b>Battery Type</b>                 | 1/AA  |
| <b>Color</b>                        | White   |
| <b>Firmware Updatable</b>           | Updatable by Consumer by RF                         |
| <b>Sensors</b>                      | Open/Closed (Binary)                                |
| <b>Supported Notification Types</b> | Access Control<br>Home Security<br>Power Management |

#### Z-Wave Product Information

|                                      |                         |
|--------------------------------------|-------------------------|
| Supports Z-Wave Beaming Technology?  | No                      |
| Supports Z-Wave Network Security?    | Yes                     |
| Supports Z-Wave AES-128 Security S0? | No                      |
| Supports Security S2?                | Yes: S2 Unauthenticated |
| SmartStart Compatible?               | No                      |

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Door/Window Sensor 7

### Z-Wave Technical Information

|  |  |
|--|--|
| <b>Z-Wave Frequency:</b>               | CEPT (Europe)                                  |
| <b>Z-Wave Product ID:</b>              | 0x0007   |
| <b>Z-Wave Product Type:</b>            | 0x0000   |
| <b>Z-Wave Hardware Platform:</b>       | ZM5101   |
| <b>Z-Wave Development Kit Version:</b> | 6.81.01  |
| <b>Z-Wave Library Type:</b>            | Enhanced 232 Slave                             |
| <b>Z-Wave Device Type / Role Type:</b> | Notification Sensor / Reporting Sleeping Slave |

### Association Group Information

**Group # / Max    Description**

**Nodes**

|       |  |
|-------|--|
| 1 / 5 | Z-Wave Plus Lifeline   |
| 2 / 5 | Control devices when magnet or external dry contacts trips                   |
| 3 / 5 | Sends our alarm message when magnet controlled or external dry sensor trips. |
| 4 / 5 | Sends alarm messages when tamper is tripped                                  |

**Supported Command Classes (18):**

|                              |                          |
|------------------------------|--------------------------|
| Association Group Info       | Association V2           |
| Battery                      | Central Scene V3         |
| Configuration                | Device Reset Locally     |
| Firmware Update Meta-Data V4 | Manufacturer Specific V2 |
| Multi-Channel Association V3 | Notification V8          |
| Powerlevel                   | Security S2              |
| Sensor Binary V2             | Supervision              |
| Transport Service V2         | Version V3               |
| Wake Up V2                   | Z-Wave Plus Info V2      |