

## Z-Wave Protocol Implementation Conformance Statement

# Gesture Controller

### General Information

**Product Identifier:** FGGC-001  
**Brand Name:** FIBARO  
**Product Version:** HW: 1 FW: 3.03:03.11  
**Z-Wave Certification #:** ZC10-19076661

### Product Features

**Battery Quantity** 4  
**Battery Type** 1,5V AA  
**Color** White

### Z-Wave Product Information

Supports Z-Wave Beaming Technology? No  
Supports Z-Wave Network Security? Yes  
Supports Z-Wave AES-128 Security S0? Yes  
Supports Security S2? No  
SmartStart Compatible? No

### Z-Wave Technical Information

**Z-Wave Frequency:** Russia  
**Z-Wave Product ID:** 0x4000  
**Z-Wave Product Type:** 0x0D01  
**Z-Wave Hardware Platform:** ZM5101  
**Z-Wave Development Kit Version:** 6.51.07  
**Z-Wave Library Type:** Enhanced 232 Slave  
**Z-Wave Device Type / Role Type:** Wall Controller / Portable Slave

### Association Group Information

Group # / Max Nodes	Description
---------------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

## (Continued)

### Gesture Controller

- 2 / 5 "Flick UP" is assigned to moving the hand up over the panel (sends Basic Set command frames).
- 3 / 5 "Flick DOWN" is assigned to moving the hand down over the panel (sends Basic Set command frames).
- 4 / 5 "Flick LEFT" is assigned to moving the hand from the right to the left side of the panel (sends Basic Set command frames).
- 5 / 5 "Flick RIGHT" is assigned to moving the hand from the left to the right side of the panel (sends Basic Set command frames) .
- 6 / 5 "Circular AirWheel" is assigned to circular move of the hand clockwise or counter-clockwise over the panel (sends Switch Multilevel Start/Stop Level Change command frames).

### Supported Command Classes (15):

Association Group Info	Association V2
Battery	Central Scene V2
Configuration	CRC16 Encapsulation
Device Reset Locally	Firmware Update Meta-Data V3
Manufacturer Specific V2	Multi-Channel Association V3
Powerlevel	Security S0
Version V2	Wake Up V2
Z-Wave Plus Info V2	

### Controlled Command Classes (3):

Basic	Central Scene V2
CRC16 Encapsulation	