

Z-Wave Protocol Implementation Conformance Statement

Gesture Controller

General Information

Product Identifier:	FGGC-001
Brand Name:	FIBARO
Product Version:	HW: 1 FW: 3.03:03.11
Z-Wave Certification #:	ZC10-19076662

Product Features

Battery Type	1,5V AA
Color	White
Battery Quantity	4

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	Hong Kong
Z-Wave Product ID:	0x9000
Z-Wave Product Type:	0x0D01
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.51.07
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Wall Controller / Portable Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Gesture Controller

- 2 / 5 "Flick UP" is assigned to moving the hand up over the panel (sends Basic Set command frames).
- 3 / 5 "Flick DOWN" is assigned to moving the hand down over the panel (sends Basic Set command frames).
- 4 / 5 "Flick LEFT" is assigned to moving the hand from the right to the left side of the panel (sends Basic Set command frames).
- 5 / 5 "Flick RIGHT" is assigned to moving the hand from the left to the right side of the panel (sends Basic Set command frames) .
- 6 / 5 "Circular AirWheel" is assigned to circular move of the hand clockwise or counter-clockwise over the panel (sends Switch Multilevel Start/Stop Level Change command frames).

Supported Command Classes (15):

Association Group Info	Association V2
Battery	Central Scene V2
Configuration	CRC16 Encapsulation
Device Reset Locally	Firmware Update Meta-Data V3
Manufacturer Specific V2	Multi-Channel Association V3
Powerlevel	Security S0
Version V2	Wake Up V2
Z-Wave Plus Info V2	

Controlled Command Classes (3):

Basic	Central Scene V2
CRC16 Encapsulation	