

Z-Wave Protocol Implementation Conformance Statement

In-Wall Smart Dimmer

General Information

Product Identifier:	39351/ZW3010
Brand Name:	Honeywell
Product Version:	HW: 255 FW: 5.53
Z-Wave Certification #:	ZC10-19086695

Product Features

Firmware Updatable	Updatable by Manufacturer
Neutral Wire Required	Yes
Z-Wave Scene Type	Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3235
Z-Wave Product Type:	0x4944
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.03
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

In-Wall Smart Dimmer

- 2 / 5 Association Group 2 supports Basic Set and is controlled by pressing the ON or OFF button with the local load
- 3 / 5 Association Group 3 supports Basic Set and is controlled by double pressing the ON or OFF button

Supported Command Classes (16):

Application Status	Association Group Info
Association V2	Basic V2
Central Scene V3	Configuration V4
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Powerlevel
Security S2	Supervision
Switch Multilevel V4	Transport Service V2
Version V3	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic V2