

## Z-Wave Protocol Implementation Conformance Statement

### Smart On/Off Switch

#### General Information

<b>Product Identifier:</b>	MS10Z
<b>Brand Name:</b>	Minoston
<b>Product Version:</b>	HW: 1 FW: 1.00
<b>Z-Wave Certification #:</b>	ZC10-19086728

#### Product Features

<b>Z-Wave Scene Type</b>	Scene
<b>Switch Type</b>	Push Button
<b>Electric Load Type</b>	Fluorescent Incandescent LED
<b>Switch Load Capacity Current</b>	15A
<b>Switch Load Capacity Watts</b>	960W
<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Consumer by RF

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Smart On/Off Switch

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0xFF03
<b>Z-Wave Product Type:</b>	0xFF01
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.81.03
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 1            Z-Wave Plus Lifeline  
2 / 5            basic set command

**Supported Command Classes (16):**

Association Group Info	Association V2
Basic V2	Central Scene V3
Configuration	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Multi-Channel Association V3	Powerlevel
Security S2	Supervision
Switch Binary	Transport Service V2
Version V3	Z-Wave Plus Info V2

**Controlled Command Classes (1):**

Basic V2