

## Z-Wave Protocol Implementation Conformance Statement

### Gerber Prime Switch

#### General Information

<b>Product Identifier:</b>	GPS-2000
<b>Brand Name:</b>	Gerber Technology 2016 Ltd.
<b>Product Version:</b>	HW: 1 FW: 1.20:01.10
<b>Z-Wave Certification #:</b>	ZC10-19086724

#### Product Features

<b>Electric Load Type</b>	Dimmable LED
<b>Z-Wave Scene Type</b>	Central Scene
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Loads Controlled</b>	4

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0073
<b>Z-Wave Product Type:</b>	0x0001
<b>Z-Wave Hardware Platform:</b>	SD3502
<b>Z-Wave Development Kit Version:</b>	6.81.03
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

## (Continued)

### Gerber Prime Switch

- 2 / 2 Group2 which correspond to relay module 1 support COMMAND\_CLASS\_SWITCH\_BINARY. The relay module 1 correspond to endpoint 1.
- 3 / 2 Group3 which correspond to smart button support COMMAND\_CLASS\_CENTRAL\_SCENE. The smart button correspond to endpoint 2.
- 4 / 2 Group4 which correspond to dimmer module 3 support COMMAND\_CLASS\_SWITCH\_MULTILEVEL. The dimmer module 3 correspond to endpoint 3.
- 5 / 2 Group5 which correspond to smart button support COMMAND\_CLASS\_CENTRAL\_SCENE. The smart button correspond to endpoint 4.
- 6 / 2 Group6 which correspond to smart button support COMMAND\_CLASS\_CENTRAL\_SCENE. The smart button correspond to endpoint 5.
- 7 / 2 Group7 which correspond to relay module 2 support COMMAND\_CLASS\_SWITCH\_BINARY. The relay module 2 correspond to endpoint 6.
- 8 / 2 Group8 which correspond to smart button support COMMAND\_CLASS\_CENTRAL\_SCENE. The smart button correspond to endpoint 7.
- 9 / 2 Group9 which correspond to dimmer module 4 support COMMAND\_CLASS\_SWITCH\_MULTILEVEL. The dimmer module 4 correspond to endpoint 8.

#### Supported Command Classes (18):

Association Group Info	Association V2
Basic	Central Scene V3
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Multi-Channel Association V3
Multi-Channel V4	Powerlevel
Security S0	Security S2
Supervision	Switch Binary
Switch Multilevel	Transport Service V2
Version V3	Z-Wave Plus Info V2

#### Controlled Command Classes (3):

Basic	Switch Binary
Switch Multilevel	