

Z-Wave Protocol Implementation Conformance Statement

Gerber Prime Switch

General Information

Product Identifier:	GPS-2000
Brand Name:	Gerber Technology 2016 Ltd.
Product Version:	HW: 1 FW: 1.20:01.10
Z-Wave Certification #:	ZC10-19086724

Product Features

Electric Load Type	Dimmable LED
Z-Wave Scene Type	Central Scene
Firmware Updatable	Updatable by Consumer by RF
Loads Controlled	4

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0073
Z-Wave Product Type:	0x0001
Z-Wave Hardware Platform:	SD3502
Z-Wave Development Kit Version:	6.81.03
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max	Description
---------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Gerber Prime Switch

- 2 / 2 Group2 which correspond to relay module 1 support COMMAND_CLASS_SWITCH_BINARY. The relay module 1 correspond to endpoint 1.
- 3 / 2 Group3 which correspond to smart button support COMMAND_CLASS_CENTRAL_SCENE. The smart button correspond to endpoint 2.
- 4 / 2 Group4 which correspond to dimmer module 3 support COMMAND_CLASS_SWITCH_MULTILEVEL. The dimmer module 3 correspond to endpoint 3.
- 5 / 2 Group5 which correspond to smart button support COMMAND_CLASS_CENTRAL_SCENE. The smart button correspond to endpoint 4.
- 6 / 2 Group6 which correspond to smart button support COMMAND_CLASS_CENTRAL_SCENE. The smart button correspond to endpoint 5.
- 7 / 2 Group7 which correspond to relay module 2 support COMMAND_CLASS_SWITCH_BINARY. The relay module 2 correspond to endpoint 6.
- 8 / 2 Group8 which correspond to smart button support COMMAND_CLASS_CENTRAL_SCENE. The smart button correspond to endpoint 7.
- 9 / 2 Group9 which correspond to dimmer module 4 support COMMAND_CLASS_SWITCH_MULTILEVEL. The dimmer module 4 correspond to endpoint 8.

Supported Command Classes (18):

Association Group Info	Association V2
Basic	Central Scene V3
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Multi-Channel Association V3
Multi-Channel V4	Powerlevel
Security S0	Security S2
Supervision	Switch Binary
Switch Multilevel	Transport Service V2
Version V3	Z-Wave Plus Info V2

Controlled Command Classes (3):

Basic	Switch Binary
Switch Multilevel	