

## Z-Wave Protocol Implementation Conformance Statement

### Ring Motion Detector (EU)

#### General Information

<b>Product Identifier:</b>	4SPA9-0EU0
<b>Brand Name:</b>	Ring
<b>Product Version:</b>	HW: 1 FW: 1.00
<b>Z-Wave Certification #:</b>	ZC10-19116786

#### Product Features

<b>Battery Quantity</b>	1
<b>Color</b>	White
<b>Battery Type</b>	CR123

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0202
<b>Z-Wave Product Type:</b>	0x0301
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.81.04
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

#### Association Group Information

Group # / Max	Description
Nodes	

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Ring Motion Detector (EU)

2 / 1                      When a node is associated with Group 2, the sensor will send a basic report of either 0xFF for “motion” or 0x00 for “no motion.”

### Supported Command Classes (15):

Association Group Info	Association V2
Basic V2	Battery
Configuration	Device Reset Locally
Manufacturer Specific	Notification V8
Powerlevel	Security S2
Supervision	Transport Service V2
Version V2	Wake Up V2
Z-Wave Plus Info V2	