

Z-Wave Protocol Implementation Conformance Statement

Z-Wave 3 in 1 Multi Sensor

General Information

| | |
|--------------------------------|----------------------|
| Product Identifier: | PST07 |
| Brand Name: | Philio Technology |
| Product Version: | HW: 1 FW: 1.02:01.02 |
| Z-Wave Certification #: | ZC10-19106767 |

Product Features

| | |
|---------------------------|---------------|
| Firmware Updatable | Not Updatable |
|---------------------------|---------------|

Z-Wave Product Information

| | |
|--------------------------------------|-------------------------|
| Supports Z-Wave Beaming Technology? | No |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | Yes |
| Supports Security S2? | Yes: S2 Unauthenticated |
| SmartStart Compatible? | Yes |

Z-Wave Technical Information

| | |
|--|--|
| Z-Wave Frequency: | CEPT (Europe) |
| Z-Wave Product ID: | 0x0070 |
| Z-Wave Product Type: | 0x0002 |
| Z-Wave Hardware Platform: | SD3502 |
| Z-Wave Development Kit Version: | 6.81.03 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | Notification Sensor / Reporting Sleeping Slave |

Association Group Information

| Group # / Max | Description |
|----------------------|---|
| Nodes | |
| 1 / 1 | Group 1 command list COMMAND_CLASS_DEVICE_RESET_LOCALLY |
| 2 / 5 | Group 2 command list COMMAND_CLASS_BASIC |

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Wave 3 in 1 Multi Sensor

Supported Command Classes (16):

Association Group Info
Battery
Device Reset Locally
Notification V8
Security S0
Sensor Multilevel V11
Transport Service V2
Wake Up V2

Association V2
Configuration
Manufacturer Specific V2
Powerlevel
Security S2
Supervision
Version V3
Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic