

## Z-Wave Protocol Implementation Conformance Statement

### Smart Plug

#### General Information

<b>Product Identifier:</b>	HKZW-SO13
<b>Brand Name:</b>	Hank
<b>Product Version:</b>	HW: 1 FW: 1.02
<b>Z-Wave Certification #:</b>	ZC10-19116791

#### Product Features

<b>Switch Load Capacity Current</b>	16A
<b>Switch Load Capacity Volt-Ampere</b>	230V
<b>Switch Load Capacity Watts</b>	3680W
<b>Firmware Updatable</b>	Updatable by Consumer via Internet
<b>Neutral Wire Required</b>	Yes
<b>Switch Type</b>	Push Button with Indicator
<b>Communications Protocol</b>	Z-Wave Serial API
<b>Color</b>	White
<b>Electric Load Type</b>	Dimmable ELV (Magnetic) Dimmable Fluorescent Dimmable LED Dimmable MLV (Magnetic) ELV (Electronic) Fluorescent Incandescent Inductive (e.g. Motor) LED MLV (Magnetic)
<b>Supported Meter Type</b>	Electric Energy

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Smart Plug

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	Yes

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0022
<b>Z-Wave Product Type:</b>	0x0100
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.81.01
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 5                    Z-Wave Plus Lifeline

**Supported Command Classes (18):**

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V3
Manufacturer Specific V2	Meter V3
Powerlevel	Scene Activation
Scene Actuator Conf	Security S0
Security S2	Supervision
Switch Binary	Transport Service V2
Version V2	Z-Wave Plus Info V2