

Z-Wave Protocol Implementation Conformance Statement

RGBW DIMMER ZEN31

General Information

Product Identifier:	ZEN31
Brand Name:	Zooz
Product Version:	HW: 2 FW: 5.00:05.00:01.00
Z-Wave Certification #:	ZC10-19126818

Product Features

Switch Load Capacity Watts	120 W at 12 VDC, 240 W at 24 VDC
Z-Wave Scene Type	Central Scene
Color	Black
Switch Load Capacity Current	10 A total (6 A per channel)

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x2000
Z-Wave Product Type:	0x0902
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.81.03
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Multilevel Switch - Color Tunable Multilevel / Always On Slave

Association Group Information

Group # / Max	Description
---------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

RGBW DIMMER ZEN31

- 2 / 5 allows to synchronize state of other Zooz RGBW Dimmers ZEN31 - do not use with other devices.
- 3 / 5 is used to turn the associated devices on/off reflecting IN1 operation.
- 4 / 5 is used to change brightness level of associated devices reflecting IN1 operation.
- 5 / 5 is used to turn the associated devices on/off reflecting IN2 operation.
- 6 / 5 is used to change brightness level of associated devices reflecting IN2 operation.
- 7 / 5 is used to turn the associated devices on/off reflecting IN3 operation.
- 8 / 5 is used to change brightness level of associated devices reflecting IN3 operation.
- 9 / 5 is used to turn the associated devices on/off reflecting IN4 operation.
- 10 / 5 is used to change brightness level of associated devices reflecting IN4 operation.

Supported Command Classes (23):

Application Status	Association Group Information V2
Association V2	Central Scene V3
Configuration	CRC16 Encapsulation
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Meter V3
Multi-Channel Association V3	Multi-Channel V4
Notification V8	Powerlevel
Protection V2	Security S0
Security S2	Sensor Multilevel V11
Supervision	Switch Color V3
Transport Service V2	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Switch Color V3