

## Z-Wave Protocol Implementation Conformance Statement

### Outdoor Smart Plug - 1 channel

#### General Information

<b>Product Identifier:</b>	MP23Z
<b>Brand Name:</b>	Minoston
<b>Product Version:</b>	HW: 255 FW: 1.255
<b>Z-Wave Certification #:</b>	ZC10-19116799

#### Product Features

<b>Color</b>	Black
<b>Electric Load Type</b>	Fluorescent Incandescent LED
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Load Capacity Watts</b>	1800W

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0xFF08
<b>Z-Wave Product Type:</b>	0xFF00
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.71.01
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	On/Off Power Switch / Always On Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Outdoor Smart Plug - 1 channel

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 5                Z-Wave Plus Lifeline

2 / 5                basic set command

**Supported Command Classes (17):**

- |                          |                              |
|--------------------------|------------------------------|
| Association Group Info   | Association V2               |
| Basic V2                 | Configuration                |
| Device Reset Locally     | Firmware Update Meta-Data V4 |
| Manufacturer Specific V2 | Multi-Channel Association V3 |
| Notification V8          | Powerlevel                   |
| Security S0              | Security S2                  |
| Supervision              | Switch Binary                |
| Transport Service V2     | Version V2                   |
| Z-Wave Plus Info V2      |                              |

**Controlled Command Classes (1):**

- Basic V2