

Z-Wave Protocol Implementation Conformance Statement

Smart Implant

General Information

| | |
|--------------------------------|----------------|
| Product Identifier: | FGBS-222 |
| Brand Name: | FIBARO |
| Product Version: | HW: 2 FW: 5.01 |
| Z-Wave Certification #: | ZC10-20036872 |

Product Features

| | |
|-------------------------------------|---|
| Sensors | (No feature option values set for this feature) |
| Supported Notification Types | (No feature option values set for this feature) |
| Color | Antique Brass |

Z-Wave Product Information

| | |
|--------------------------------------|---|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | Yes |
| Supports Security S2? | Yes: S2 Authenticated, S2 Unauthenticated |
| SmartStart Compatible? | Yes |

Z-Wave Technical Information

| | |
|--|---------------------------------------|
| Z-Wave Frequency: | South Korea |
| Z-Wave Product ID: | 0xB000 |
| Z-Wave Product Type: | 0x0502 |
| Z-Wave Hardware Platform: | ZM5101 |
| Z-Wave Development Kit Version: | 6.81.01 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | Notification Sensor / Always On Slave |

Association Group Information

| Group # / Max | Description |
|---------------|-------------|
| Nodes | |

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart Implant

2 / 5 is assigned to IN1 input terminal (uses Basic command class).

3 / 5 is assigned to IN2 input terminal (uses Basic command class).

Supported Command Classes (23):

| | |
|------------------------------|----------------------------------|
| Application Status | Association Group Information V2 |
| Association V2 | Basic |
| Central Scene V3 | Configuration |
| CRC16 Encapsulation | Device Reset Locally |
| Firmware Update Meta-Data V4 | Manufacturer Specific V2 |
| Multi-Channel Association V3 | Multi-Channel V4 |
| Notification V8 | Powerlevel |
| Protection V2 | Security S0 |
| Security S2 | Sensor Multilevel V11 |
| Supervision | Switch Binary |
| Transport Service V2 | Version V2 |
| Z-Wave Plus Info V2 | |

Controlled Command Classes (1):

Basic