

## Z-Wave Protocol Implementation Conformance Statement

# Recessed Door Sensor 7

### General Information

<b>Product Identifier:</b>	ZW187-C
<b>Brand Name:</b>	Aeotec
<b>Product Version:</b>	HW: 187 FW: 1.04
<b>Z-Wave Certification #:</b>	ZC12-20010026

### Product Features

<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Battery Quantity</b>	1
<b>Battery Type</b>	CR2

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x00BB
<b>Z-Wave Product Type:</b>	0x0002
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.12.2
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Reporting Sleeping Slave

### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Recessed Door Sensor 7

2 / 5 Issue Basic Set when Magnet is away or near. (The Basic Set Value is determined by Configuration Parameter 3)

### Supported Command Classes (20):

Application Status	Association Group Information V3
Association V2	Battery
Configuration V4	Device Reset Locally
Firmware Update Meta-Data V5	Indicator V3
Manufacturer Specific V2	Multi-Channel Association V3
Notification V8	Powerlevel
Security S0	Security S2
Sensor Binary V2	Supervision
Transport Service V2	Version V3
Wake Up V2	Z-Wave Plus Info V2