



## Z-Wave Protocol Implementation Conformance Statement

# Plug-in Switch (Dual Plug Simultaneous Control)

### General Information

<b>Product Identifier:</b>	39449 / ZW4106
<b>Brand Name:</b>	Honeywell
<b>Product Version:</b>	HW: 255 FW: 5.22
<b>Z-Wave Certification #:</b>	ZC10-19126812

### Product Features

<b>Color</b>	White
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Loads Controlled</b>	2
<b>Switch Load Capacity Current</b>	15
<b>Switch Load Capacity Watts</b>	1800
<b>Switch Type</b>	Push Button Illuminated

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3033
<b>Z-Wave Product Type:</b>	0x5052
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.10
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Plug-in Switch (Dual Plug Simultaneous Control)

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

- 1 / 5                Supports Device Reset Locally and receives unsolicited status updates
- 2 / 5                Association Group 2 supports Basic Set and is controlled by single pressing the button
- 3 / 5                Association Group 3 supports Basic Set and is controlled by double pressing the button

**Supported Command Classes (15):**

- |                              |                          |
|------------------------------|--------------------------|
| Association Group Info       | Association V2           |
| Basic                        | Configuration            |
| CRC16 Encapsulation          | Device Reset Locally     |
| Firmware Update Meta-Data V2 | Manufacturer Specific V2 |
| Powerlevel                   | Scene Activation         |
| Scene Actuator Conf          | Switch All               |
| Switch Binary                | Version V2               |
| Z-Wave Plus Info V2          |                          |

**Controlled Command Classes (1):**

- Basic