

## Z-Wave Protocol Implementation Conformance Statement

### Plug-in Outdoor Switch

#### General Information

<b>Product Identifier:</b>	39346 / ZW4201
<b>Brand Name:</b>	Honeywell
<b>Product Version:</b>	HW: 255 FW: 5.21
<b>Z-Wave Certification #:</b>	ZC10-19126817

#### Product Features

<b>Color</b>	Black
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Outdoor Use</b>	Yes
<b>Switch Load Capacity Current</b>	15
<b>Switch Load Capacity Watts</b>	1800
<b>Switch Type</b>	Push Button

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3032
<b>Z-Wave Product Type:</b>	0x4F50
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.10
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Plug-in Outdoor Switch

### Association Group Information

**Group # / Max    Description**

**Nodes**

- 1 / 5                Supports Device Reset Locally and receives unsolicited status updates.
- 2 / 5                Association Group 2 supports Basic Set and is controlled by single pressing the button.
- 3 / 5                Association Group 3 supports Basic Set and is controlled by double pressing the button

**Supported Command Classes (14):**

Association Group Info	Association V2
Basic	CRC16 Encapsulation
Device Reset Locally	Firmware Update Meta-Data V2
Manufacturer Specific V2	Powerlevel
Scene Activation	Scene Actuator Conf
Switch All	Switch Binary
Version V2	Z-Wave Plus Info V2

**Controlled Command Classes (1):**

Basic