

Z-Wave Protocol Implementation Conformance Statement

S100 Rocker for Dimmer (Mexico)

General Information

Product Identifier:	10005020-13x
Brand Name:	Simon
Product Version:	HW: 1 FW: 4.24:78.59:70.48
Z-Wave Certification #:	ZC10-20016852

Product Features

Switch Load Capacity Watts	240
Firmware Updatable	Updatable by Professional/Technician
Electric Load Type	Dimmable ELV (Magnetic) Dimmable LED Dimmable MLV (Magnetic) Incandescent

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0000
Z-Wave Product Type:	0x0007
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.07
Z-Wave Library Type:	Enhanced Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

S100 Rocker for Dimmer (Mexico)

Association Group Information

Group # / Max **Description**

Nodes

- 1 / 3 On/Off Report when load state is changed: - On -> CC Basic, Basic Report, Value 0x01 - 0x63 Report the dimming level - Off -> CC Basic, Basic Report, Value 0x00 Instant Power Consumption vary over 10% and is stable almost 2sec - CC Meter, Meter Report, "Electric meter", "Consumed", "Watts", Size 4, Precision 1, Value (W) Calibration requirement change. (If device needs to be calibrated and is Added into a Z-Wave network, it will report after receive an Association Set of life line). - Calibration required -> CC Configuration, Configuration Report, Param 23, Value 0xFF - Calibration not required -> CC Configuration, Configuration Report, Param 23, Value 0x00 After reset the Z-Wave module, a DEVICE-RESET-LOCALLY-NOTIFICATION is sent.
- 2 / 20 On/Off Report when load state is changed:

Supported Command Classes (12):

- | | |
|----------------------------------|------------------------------|
| Association Group Information V3 | Association V2 |
| Basic | Configuration V2 |
| Device Reset Locally | Firmware Update Meta-Data V4 |
| Manufacturer Specific V2 | Meter V4 |
| Powerlevel | Switch Multilevel V3 |
| Version V2 | Z-Wave Plus Info V2 |