

Z-Wave Protocol Implementation Conformance Statement

S100 Rocker for Roller Blind (Russia)

General Information

Product Identifier:	10004080-13x
Brand Name:	Simon
Product Version:	HW: 1 FW: 4.24:75.53:66.47
Z-Wave Certification #:	ZC10-20016842

Product Features

Window Covering Control Features	Automatic Calibration
Neutral Wire Required	Yes
Firmware Updatable	Updatable by Professional/Technician
Switch Load Capacity Volt-Ampere	700

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	Russia
Z-Wave Product ID:	0x0000
Z-Wave Product Type:	0x0004
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.07
Z-Wave Library Type:	Enhanced Slave
Z-Wave Device Type / Role Type:	Window Covering - Pos/End Aware / Always On Slave

Association Group Information

Group # / Max	Description
---------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

S100 Rocker for Roller Blind (Russia)

2 / 20 Ctrl When Touch area is detected o key is pressed without touch area detection: CC Configuration, Configuration Get, Param 21 -> Sent if param 28 value is 0x00, there is only 1 device is associated and it is a Simon device. Used to know the associated device state. CC Basic, Basic Get -> Sent if param 28 value is 0x00, there is only 1 device is associated and it is not a Simon device. Used to know the associated device state. COMMAND_CLASS_BASIC_REPORT Associates are sent when the sunblind remains stoped for 1.5s after changing positions. % New position -> CC Basic, Basic Report, Value 0x00 - 0x63

Supported Command Classes (12):

Association Group Information V3	Association V2
Basic	Configuration V2
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Powerlevel
Switch Binary	Switch Multilevel V3
Version V2	Z-Wave Plus Info V2