

## Z-Wave Protocol Implementation Conformance Statement

### Zerodim Z-Wave

#### General Information

<b>Product Identifier:</b>	1414141
<b>Brand Name:</b>	Q-light
<b>Product Version:</b>	HW: 255 FW: 4.03
<b>Z-Wave Certification #:</b>	ZC10-20036887

#### Product Features

<b>Color</b>	White
<b>Firmware Updatable</b>	Not Updatable
<b>Neutral Wire Required</b>	Yes
<b>Z-Wave Scene Type</b>	Central Scene

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x000D
<b>Z-Wave Product Type:</b>	0x0003
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.81.06
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Light Dimmer Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Zerodim Z-Wave

2 / 5            Mirror of endpoint 1, group 2.

3 / 5            Mirror of endpoint 1, group 3.

### Supported Command Classes (20):

Association Group Info

Basic V2

Device Reset Locally

Manufacturer Specific V2

Multi-Channel V4

Powerlevel

Scene Actuator Conf

Security S2

Switch Multilevel V4

Version V3

Association V2

Configuration

Firmware Update Meta-Data V4

Multi-Channel Association V3

Notification V8

Scene Activation

Security S0

Supervision

Transport Service V2

Z-Wave Plus Info V2

### Controlled Command Classes (2):

Basic V2

Switch Multilevel V4