

## Z-Wave Protocol Implementation Conformance Statement

# Z-Wave Relay Dimmer switch

### General Information

<b>Product Identifier:</b>	ZW34
<b>Brand Name:</b>	Zooz
<b>Product Version:</b>	HW: 2 FW: 1.00
<b>Z-Wave Certification #:</b>	ZC10-20016827

### Product Features

<b>Color</b>	White
<b>Electric Load Type</b>	Dimmable LED Fluorescent Incandescent Inductive (e.g. Motor)
<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Type</b>	Push Button

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0xa008
<b>Z-Wave Product Type:</b>	0xa000
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.82.00
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Light Dimmer Switch / Always On Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Z-Wave Relay Dimmer switch

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 1	Z-Wave Plus Lifeline
2 / 5	basic set command
3 / 5	basic set command

**Supported Command Classes (18):**

Association Group Info	Association V2
Basic V2	Central Scene V3
Configuration	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Multi-Channel Association V3	Multi-Channel V4
Powerlevel	Security S2
Supervision	Switch Binary
Switch Multilevel V4	Transport Service V2
Version V3	Z-Wave Plus Info V2

**Controlled Command Classes (1):**

Basic V2