



Z-Wave Protocol Implementation Conformance Statement

Double-Switch

General Information

Product Identifier: 0x00/9498
Brand Name: TechniSat
Product Version: HW: 6 FW: 2.00
Z-Wave Certification #: ZC10-20036884

Product Features

Firmware Updatable Updatable by Consumer by RF
Neutral Wire Required Yes

Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? Yes
Supports Security S2? Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible? Yes

Z-Wave Technical Information

Z-Wave Frequency: CEPT (Europe)
Z-Wave Product ID: 0x1A91
Z-Wave Product Type: 0x0003
Z-Wave Hardware Platform: ZM5101
Z-Wave Development Kit Version: 6.82.00
Z-Wave Library Type: Enhanced 232 Slave
Z-Wave Device Type / Role Type: On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 1	The lifeline group reports the device's status.

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Double-Switch

- 2 / 10 Sends basic set commands according to the current state of switch 1 of the device to associated devices.
- 3 / 10 Sends basic set commands according to the current state of switch 2 of the device to associated devices.

Supported Command Classes (20):

- | | |
|------------------------------|------------------------------|
| Association Group Info | Association V2 |
| Basic V2 | Central Scene V3 |
| Configuration | Device Reset Locally |
| Firmware Update Meta-Data V4 | Manufacturer Specific V2 |
| Meter V4 | Multi-Channel Association V3 |
| Multi-Channel V4 | Notification V8 |
| Powerlevel | Security S0 |
| Security S2 | Supervision |
| Switch Binary | Transport Service V2 |
| Version V3 | Z-Wave Plus Info V2 |

Controlled Command Classes (1):

- Basic V2